

Site Intercept

303 Darren M Mon, Feb 15, 2021 [Site / Company Features](#) 990

Site Intercept

Description

Typically this feature allows calls routed to a line that has been decommissioned to be intercepted with an informative announcement and alternate routing options (for example, **“This number is no longer in service. To talk to an operator, press 0”**). This feature can only be configured by CP Administrators.

The feature may be used to decommission a single User, or an entire Site. Please refer to ‘User Intercept’ section in the IC-Talk 3 User Features Guide.

Function

If the Site Intercept feature is assigned to a Site and configured, then incoming calls to the Site are intercepted and played an announcement. If configured, this announcement plays back a new destination number to the caller and offers the caller to connect to this new number or to simply transfer to an alternate destination.

Outgoing calls are prohibited from a User when the Site Intercept feature is configured. Only emergency and repair calls are permitted. All other outgoing call attempts are rejected and the User is played an announcement.

The Site Intercept feature allows three types of incoming call interception:

- **Static** - An out-of-service announcement is played twice followed by a fast busy treatment.
- **Hear new destination** - The out-of-service announcement is complemented with the playback of the User’s new phone number.
- **Connect to new destination** - After hearing the new phone number, the caller can press a ‘0’ to be immediately transferred to the configured destination.

Configuration

Site Intercept feature can only be configured by:

- Navigate to the Sites tab (Select Site) > Features > Site Intercept
- To activate Site Intercept, tick the **Turn on Site Intercept**
- This will provide an out of service announcement followed by fast busy tone.

The screenshot shows the 'Site Intercept' configuration interface. At the top, the title 'Site Intercept' is displayed. Below it, there are several settings:

- Turn On Site Intercept (highlighted with a red box)
- Announce New Telephone Number
- New Telephone Number**: Telephone Number (input field)
- Transfer On '0'
- Transfer To**: Telephone Number (input field)
- Use Personal Announcement
- Current Audio File**: chu24.wav
- Upload Audio File**: Choose File No file chosen (input field)

 At the bottom, there are two buttons: 'Cancel' (orange) and 'Save' (green). Below the 'Upload Audio File' field, there is a small note: 'File type is CCITT u-Law WAV with 8kHz, 8Bit, Mono attributes.'

If you want your new phone number to be provided to callers, select the **Announce New Telephone Number** check box and enter the required phone number into the **New Phone Number** field.

The screenshot shows the 'Site Intercept' configuration interface. At the top, the title 'Site Intercept' is displayed. Below it, there are several settings:

- Turn On Site Intercept
- Announce New Telephone Number (highlighted with a red box)
- New Telephone Number**: Telephone Number (input field, highlighted with a red box)
- Transfer On '0'
- Transfer To**: Telephone Number (input field)
- Use Personal Announcement
- Current Audio File**: chu24.wav
- Upload Audio File**: Choose File No file chosen (input field)

 At the bottom, there are two buttons: 'Cancel' (orange) and 'Save' (green). Below the 'Upload Audio File' field, there is a small note: 'File type is CCITT u-Law WAV with 8kHz, 8Bit, Mono attributes.'

If you want callers to be given the option to be transferred to another phone number when they press the '0' key, select the **Transfer on '0'** check box and enter the number to which callers are to be transferred in the **Transfer To** box.

Site Intercept

Turn On Site Intercept

Announce New Telephone Number

New Telephone Number

Transfer On 'D'

Transfer To

Use Personal Announcement

Current Audio File

Upload Audio File

File type is CCITT u-Law WAV with 8kHz, 8Bit, Mono attributes.

If you want callers to hear a personal announcement that you have recorded and stored in a WAV format file rather than a standard system announcement, select the 'Use Personal Announcement' check box and click Browse to select the file.

The file you select must be a CCITT-compliant, μ -Law-encoded, 8-bit WAV file with mono sound, a maximum sample rate of 8 kHz, and a maximum file size uploaded through the Business Portal of 1 MB.

- Click **Save**

NOTE: The maximum recording length for the Site Intercept and User Intercept announcements is five minutes and file size must be less than 1MB.

Limiting Conditions

On a Site that has the Site Intercept feature enabled, Users cannot place outgoing calls,

with the exception of emergency calls.

If a User has User Intercept enabled and configured this will override the Site Intercept announcement and the configured destination.

Online URL: <https://kb2.ic.uk/article.php?id=303>