# Device Management (Information)

337 Darren M Mon, Feb 15, 2021 Site / Company Features 678

## **Device Management (Information)**

## Description

The Device Management feature provides the Group or Company Administrator with an inventory of all Devices in a Site and the ability to manage and customize these devices.

These Devices may include integrated access devices (IAD), Softphones and IP phones for Centrex services. For SIP Trunking sites, SIP Devices such as PBXs, Media Gateways and SBCs will be listed along with any Enterprise Trunks configured.

In addition, this feature provides the capability to assign Users directly to an existing device without the need for de-provisioning the User. The Group or Company Administrator can use the Device Inventory to create, modify, and delete the IP telephones that are used within a given Site.

## Function

This feature allows the Group or Company Administrator to keep track of the Devices (gateways, IP phones, PBXs etc), used by the Site. By default, the Device Inventory page automatically lists all devices that are currently in use within the selected Site.

This allows the Group or Company Administrator to add new devices to be used in conjunction with User features such as 'Shared Call Appearance' or Delete devices no longer in use at one Site for re-use on another Site.

Deleting a Device that is no longer assigned to a User will reopen the MAC address of the device for re-use elsewhere.

The Device Inventory shows the following information:

- Device Name The default device name created when a User is activated and assigned a device is the Enterprise ID plus the Username.
- Device Type This shows the device that was selected from the drop down list

when the User was activated.

• Available Lines/Ports - This shows the number of ports that are not yet used on that particular device. For example a Polycom SoundPoint IP 500 has 4 available lines. If this assigned to a User, one line will be Used and the 'Available Lines/Ports' column will show 3. If this User has Additional Lines or Shared Call Appearances assigned to their device, the 'Available Line/Ports' column will drop accordingly.

Devices												+ Add			
50 Devices found. Displaying 1 to 20									1 2	3					
	Baudan Roma	Device Type	Available Lines/Ports		ACO	ACO BLF		Codec							
	Device Name			MAC Address	On	On	6711	6729	ю	<b>0</b> 1	011				
	100000141chris.zimmer 🖊	UC Office Desktop	8	441514960033								s 5			
	100000141 every feature 🖉	UC Office Desktop	6	441514960000		0						N 0			
	100000141sca.05 🖋	Cisco SPA-512G	0	441514960019								N 0			
	100000141sca.10 🖌	Cisco SPA-514G	3	441514960017		$\bigcirc$				Ο		N 0			
	100000141user.name 🖋	UC Office Desktop	9	441154960018		0				Ο		N 0			
		Cisco SPA-112	2	AAAAAAAB880C		0			0			N 0			
	android phone 1 🖌	MobileOffice Android Phone	9	145874587458		0						N 0			
	android phone1 🖊	MobileOffice Android Phone	10	478541215AAA		0				$\bigcirc$		N 0			
	chrisSCA01 🖉	Cisco SPA-112	1	01514960033A		0			0			<b>N</b> D			
	chriszimmer2_UCOfficeDesktop /	UC Office Desktop	9									<b>N</b> D			

## Configuration

#### **Configuration – Add a Device**

The Group or Company Administrator can use the Device Inventory to Add a new Device to a Site.

- Navigate to: Sites (select Site) > Device Management > Devices
- Click 'Add'

• The New Device page is displayed.

New Device	×
* Device ID	Device ID
Device Type	Cisco SPA-112
IP Address	IP Address
Port	Port
MAC Address	MAC Address
Serial Number	Serial Number
Description	IP Phone
Ø Cancel	✓ Save

- Enter the required information
  - Device ID Enter an ID for the Device
  - Device Type select the required Device Type from the those available in the drop down list
  - MAC Address Enter the MAC address of the Device. If the device is a type that does not have a MAC address, for example, a softphone, please enter the phone number in E164 format.

Other fields are optional on the IC-Talk 3 platform. Enter information as required.

• Click Save

The Devices page is displayed with the New Device added to the list.

#### **Configuration – Modify a Device**

Navigate to: Sites (select Site) > Device Management > Devices

•	Click on	the name	of the	device	you	want to	modify
---	----------	----------	--------	--------	-----	---------	--------

Devi	ces										+	Add
50 De	0 Devices found. Displaying 1 to 20									1 2	3 , ,	
	Davies Home			MAC Address	ACD BLF		Codec			DC	MCN	
	Device name	Device type	Available Lines/Fulls		On	On	G711	G729	но	On	011	
0	100000141chris.zimmer 🖋	UC Office Desktop	8	441514960033			0	0	0	$\Box$		° 0
0	100000141every.feature 🖉	UC Office Desktop	6	441514960000			0	0	0	$\Box$		s 5
0	100000141sca.05 🖋	Cisco SPA-512G	0	441514960019	$\Box$		0	0	0	$\bigcirc$		s 5
0	100000141sca.10 🖋	Cisco SPA-514G	3	441514960017	$\Box$	$\bigcirc$	0	0	0	$\bigcirc$		s 5
0	100000141user.name 🖋	UC Office Desktop	9	441154960018			0	0	0	$\bigcirc$		s 5
0	2022020202020202	Cisco SPA-112	2	AAAAAAABBBC			0	0	0	0		s 5
0	android phone 1 /	MobileOffice Android Phone	9	145874587458			0	0	0	0		s 5
0	android phone 1 🖊	MobileOffice Android Phone	10	478541215AAA			0	0	0	$\bigcirc$		s 5
0	chrisSCA01 🖋	Cisco SPA-112	1	01514960033A			0	0	0	$\Box$		s 5
0	chriszimmer2_UCOfficeDesktop 🖋	UC Office Desktop	9				0	0	0	$\Box$		s 5

• Modify the fields as required.

You cannot modify the Device ID, Device Type, Assigned Lines, Lines, or Available Lines fields.

Modify Device	×	]
Device ID	100000141chris.zimmer	
Device Type	UC Office Desktop	
IP Address	IP Address	
Port	Port	
* MAC Address	441514960033	
Serial Number	Serial Number	
Description		
Available Lines/Ports	8 / 10	
⊘ Cancel	✓ Save	

• Click Save

### **Configuration – Delete a Device**

You *cannot* delete a Device with a port that is in use or has been assigned for use.

- Navigate to: Sites (select Site) > Device Management > Devices
- Select the radio button of the device you want to delete.

Devices								+ Add					
50 De	50 Devices found. Displaying 1 to 20										1 2	3	, ,
	Burden Name		Aurilable Lines Berte	MAC Address	ACD	BLF	Codec			DC	MCN		
	Device Name	Device type	Available Lines/Ports		On	On	6711	G729	HD	On	off		
۲	100000141chris.zimmer 🖋	UC Office Desktop	8	441514960033			0	0	0	0		8	р
0	100000141every.feature 🖉	UC Office Desktop	6	441514960000			0	0	0	$\bigcirc$		8	5
0	100000141sca.05 🖋	Cisco SPA-512G	0	441514960019	$\bigcirc$		0	0	0	$\bigcirc$		8	р.
0	100000141sca.10 🖋	Cisco SPA-514G	3	441514960017	$\Box$	$\Box$	0	0	0	$\bigcirc$		۰.	р.

• Click Delete.

Online URL: <u>https://kb2.ic.uk/article.php?id=337</u>